

## DET-6C



### FEATURES

- Rugged cottage shell housing
- Solid-state telegraph transmitter
- Low power consumption
- Programmable to match existing number of rounds, transmission speed, box number, etc.
- AC or DC powered
- 6 Channel EOL with separate code for each channel
- Open or Closed index
- Watchdog Timer for failure detection & notification
- Form C trouble relay
- Low battery and Tamper
- Internal buzzer for alarm/trouble
- Prioritized by zone and alarm/trouble
- Precodes
- Dual 6-zone version (total 12 zones) available
- NFPA-72 Compliant

### Product Description

The DET-6-C is a 6-channel EOL transmitter in cottage shell housing. It includes a CAM loc, AC transformer, standby battery, and built-in charger. The unit is housed in a durable cottage shell enclosure suitable for outdoor mounting.

Telegraph codes unique to each of the six zones for Trouble, Alarm, Secure, as well as Tamper and Low Battery are transmitted over 100 milliamperere circuit using positive non-interfering successive (PNIS) line current detection to avoid clashes between more than one transmitting box. Automatic ground return, a watchdog timer, and a jumper selected internal trouble buzzer assure continued main system operation and operator notification in the event of box failure. A built-in trouble relay output (form C) and the ground and code relay (grounding, opening, or no effect on the 100MA line) are activated by the watchdog timer ensuring reliable failure detection in the event of malfunction.

Transmission speed is adjustable to match that of mechanical boxes. Unit can be programmed to send any number of rounds (or no rounds) on alarm, trouble, secure and low battery.

Automatic switchover to battery power is performed upon AC power loss with a low battery code transmitted if power is not returned in approximately 50 hours. After transmitting a low battery code, the unit bypasses all input circuits to avoid spurious transmissions of false alarms.

The DET-6C is field programmable with optional EPROM programmer and PC software. A dual 6-zone version (total of 12 zones) is also available.

A master trip module is available for connection to an interior FACP.

Use of lightning protection is recommended for DET-6C and DET-12C.



## SPECIFICATIONS

---

### DIMENSIONS

Height: 17.5 in.  
Depth: 6.0 in.  
Width: 12.5 in.

### POWER

- 124 VA 50/60 Hertz with no step down transformer
- 24 VDC or 12 VDC (separate terminals)
- 100MA standby, 170 MA operating.

### INPUT CHANNEL ACTIVATION

6 Channels EOL resistor (5.6 K)  
1 for Fire Hook  
2 Channels with Reed Input  
Low Battery Detection

### VISIBLE LED INDICATORS

Main Power: Green  
Trouble: Red  
Watchdog: Red  
On-line: Red (transmitting)

### BUZZER

0-9.9 minutes (jumper selected On/Off)

### TRANSMISSION SPEED

1/24 second increments from 1/8 to 4 seconds

### OUTPUT

- 1-6 Telegraph codes, program each zone
- 4 Supervisory codes for a total of 10 codes
- Open or Ground telegraph line on failure (or local failure)
- Form C Trouble Relay

---

### Ordering Information:

425101-0000 DET-6C without pole mounting  
425101-0001 DET-6C with pole mounting  
425401-0003 DET-12-C without pole mounting  
425101-0004 DET-12C with pole mounting  
010001-0021 DET-PORG, PC software with programmer



DET-6C